

Technical Specifications and Register Map For

mLink NTC Temperature Sensor
Module (HCMODU0186)

DISCLAIMER

The mLink range is a series of modules intended for the hobbyist and educational markets. Where every care has been taken to ensure the reliability and durability of this product it should not be used in safety or reliability critical applications.

This document is provided "as is". Hobby Components Ltd makes no warranties, whether express, implied or statutory, including, but not limited to, implied warranties of merchantability and fitness for a particular purpose, accuracy or lack of negligence. Hobby Components Ltd shall not, in any circumstances, be liable for any damages, including, but not limited to, special, incidental or consequential damages for any reason whatsoever.

COPYRIGHT NOTICE

This manual, including content and artwork is copyright of Hobby Components Ltd and may not be reproduced without written permission. If you paid for or received a copy of this manual from a source other than Hobby Components Ltd, please contact us at sales@hobbycomponents.com

Specifications

Module specifications:

Module code:	HCMODU0186
Supply Voltage (VDD):	3.3V to 5.5V
Operating range (recommended):	-5 to 105oC
Temperature resolution:	$\pm 0.7^{\circ}\text{C}$ @ 0°C $\pm 0.1^{\circ}\text{C}$ @ 25°C $\pm 1.5^{\circ}\text{C}$ @ 100°C
Current consumption (idle):	5.6mA
Current consumption (sleep):	0.5mA
Interfaces:	I2C, NTC (10K 3950) sensor
I2C Interface speed:	400kbits/s (fast mode)
I2C default address (HEX):	0h54
Maximum number of modules:	5 with pullups fitted, 112 with pullups removed*
Module dimensions (inc headers):	40mm x 10.6mm x 10mm (sensor not fitted)

*Note the maximum number of connected modules will depend on cable lengths and power requirements of each module. Do not exceed 5 mLink modules connected in series with all pullups fitted.

NTC sensor specifications:

Operating range:	-20 to 105oC *
Type:	NTC 10K 3950
Accuracy:	+/-1% (10K) **
Probe insulation:	>100MOhm
Sensor material:	Stainless steel waterproof
Cable length:	2 metres

* See module specifications for recommended operating range

**Sensor accuracy is limited by the module's resolution. See module specification or module resolution table in this document.

Register Map

Register quick reference table

REGISTER	REG ADD	Reg Bit 7	Reg Bit 6	Reg Bit 5	Reg Bit 4	Reg Bit 3	Reg Bit 2	Reg Bit 1	Reg Bit 0
STATUS	0h00	RESERVED					BUSY	REGERR	I2CERR
I2C ADD (Def = 0h51)	0h01	RESERVED	I2CADD						
MODULE TYPE	0h02	0h01							
MODULE SUBTYPE	0h03	0h00							
FIRMWARE VERSION	0h04	0hXX							
SLEEP	0h05	RESERVED							SLEEPEN
RESERVED	0h06 to 0h0A	RESERVED							
NTC TEMP LOW	0h0B	TEMP[7:0]							
NTC TEMP HIGH	0h0C	TEMP[15:8]							

Status register

Register address: 0h00

Default value: 0

7	6	5	4	3	2	1	0
RESERVED					BUSY	REGERR	I2CERR
r					r	rw	rw

Bits 7:3 Reserved

Bit 2 **BUSY**: Busy status

This bit is set and reset by hardware

0: Measurement ready

1: Measurement in progress

Bit 1 **REGERR**: Register access error

This bit is set by hardware and reset by software

0: No register access error

1: Register access error caused by attempting to access a non-existent register, writing an illegal value to a register, or writing to a read only register

Bit 0 **I2CERR**: I2C bus access error

This bit is set by hardware and reset by software

0: No I2C error

1: An I2C bus error has occurred

Writing any value to this register will clear all bits

I2C Address Register

Register address: 0h01

Default value: 0h54

7	6	5	4	3	2	1	0
N/A	I2CADD						
r	rw						

Bit 7 N/A: Returns 0

Bits 6:0 **I2CADD**: 7 bit I2C address (default factory reset value = 0h54)

These bits are set by software

Values written to this register will be stored in non-volatile memory

Valid address range is 0h08 to 0h77. Addresses outside this range will be ignored but will set the **REGERR** bit in the status register.

Before a new address can be written to this register it must first be unlocked by writing bytes 0x55 followed by 0xAA. The new address byte must then be written within 100ms of writing the 0xAA byte otherwise the unlock process will timeout and reset.

Module Type Register

Register address: 0h02

Default value: 0h04

7	6	5	4	3	2	1	0
MTYP							
r							

Bits 7:0 **MTYP**: 8 bit value representing the module type.

This register will always return 0h04 signifying this module type is 'Temperature'

Module Subtype Register

Register address: 0h03

Default value: 0h00

7	6	5	4	3	2	1	0
STYP							
r							

Bits 7:0 **STYP**: 8 bit value representing the module subtype.

This register will always return 0h00 signifying this module subtype is 'NTC'

Firmware Version Register

Register address: 0h04

Default value: 0hXX

7	6	5	4	3	2	1	0
FWMMAV				FWMIV			
r				r			

Bits 7:4 **FWMMAV**: 4 bit value representing the modules major firmware version

Bits 3:0 **FWMIV**: 4 bit value representing the modules minor firmware version

Sleep Register

Register address: 0h05

Default value: 0h00

7	6	5	4	3	2	1	0
RESERVED							SLEEPEN
w							

Bits 7:1 Reserved

Bit 0 **SLEEPEN**: Sleep enable

This bit is set by software. Writing a 1 to this bit will place the module into low power sleep mode.

1: Enable sleep mode

Sleep mode is exited (SLEEPEN = 0) automatically on the next register read or write.

Note: After exiting sleep mode the busy bit in the status register should be polled before reading a new temperature.

NTC Temp Low Register

Register address: 0h0B

Default value: 0h00

7	6	5	4	3	2	1	0
TEMP[7:0]							
r							

Bits 7:0 **TEMP[7:0]**: NTC temperature low byte.

This register is set by hardware.

The NTC Temp low register together with the NTC Temp high register store the last measured temperature as a 16 bit 2's complement value shifted by 1 decimal place to the left. Therefore to get the correct value read the two registers as a 16 bit two complement value then divide by 10 to get the temperature (in °C) to 1 decimal place.

NTC Temp High Register

Register address: 0h0C

Default value: 0h00

7	6	5	4	3	2	1	0
TEMP[15:8]							
r							

Bits 15:8 **NTC[15:8]**: NTC temperature high byte.

This register is set by hardware.

The DHT Temp high register together with the DHT Temp low register store the last measured temperature as a 16 bit 2's complement value shifted by 1 decimal place to the left. Therefore to get the correct value read the two registers as a 16 bit two complement value then divide by 10 to get the temperature (in °C) to 1 decimal place.